



- Professional multi-functional 12V lithium starter. 2000A start max.
- With high performance batteries; fast, full charge thanks to the high efficiency LiPo lithium polymer cells.
- Two USB outputs (1A-2,1A) to charge electronic devices (tablet, smartphone, etc.).
- Powerful lighting source. 2 high intensity led lights and 3 operating modes.
- Compact but light; strong thanks to anti-shock cover.
- Protection against pole inversion.

TECHNICAL DATA

| | | | | | |
|--------------------------|--------------------|------------------------|---------------|------------------------|-----------------------|
| CODE | 829572 | STARTING CURRENT | 600 A | OUTPUT CURRENT #2(USB) | 2,1 A |
| CHARGE MAINS VOLTAGE 1ph | 100 - 240 V | MAX STARTING CURRENT | 2000 A | DIMENSIONS (LxWxH) | 21 x 12 x 7 cm |
| CHARGE MAINS FREQUENCY | 50 / 60 Hz | OUTPUT VOLTAGE #1(USB) | 5 V | WEIGHT | 1,1 kg |
| BATTERY CAPACITY | 12000 mAh | OUTPUT CURRENT #1(USB) | 1 A | | |
| STARTING VOLTAGE | 12 V | OUTPUT VOLTAGE #2(USB) | 5 V | | |

SUPPLIED ACCESSORIES

| | |
|--------|---------------------|
| 125182 | JUMP STARTER CABLES |
| 125183 | CAR CHARGER CABLE |
| 168047 | POWER SUPPLY |

DESCRIPTION

Multifunction 12V lithium starter, equipped with:

- two USB outputs (1A-2,1A) to charge (power bank) electronic devices (tablets, smartphones, etc.),
- high intensity LED lights with three function modes for fixed or emergency lighting.

It uses high-efficiency LiPO lithium polymer cells that provide rapid and complete charging, constantly monitored by a series of LEDs.

Compact and strong it is designed for the professional use.

Protection against polarity reversal.

Complete with starting cables, cigarette lighter plug and wall charge.

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL